

**AMENDMENTS TO THE CLAIMS:**

This listing of the claims will replace all prior versions, and listings, of the claims in this application.

**Listing of Claims:**

1. (Previously Presented) A method for performing an interference estimation in a spread spectrum system using a plurality of spreading codes with different code lengths, comprising the steps of:

- a) receiving a spread spectrum signal;
- b) generating a despread sample signal by averaging over a predetermined code period over which said plurality of spreading codes are orthogonal;
- c) calculating a variance estimate based on said despread sample signal; wherein said variance estimate is calculated by:

integrating said despread sample signal over a spreading code length of said received spread spectrum signal;

integrating a signal corresponding to a power of said despread sample signal over said plurality of spreading code lengths; and

subtracting a signal obtained by squaring an output signal of said integration of said despread sample signal from an output signal of said integration of the signal corresponding to the power of said despread signal.

2. (Previously Presented) The method according to claim 1, wherein said variance estimate is calculated by averaging said despread sample signal over a spreading code length of said received spread spectrum signal.

<sup>5</sup>  
~~7~~. (Previously Presented) The method according to claim 1, wherein said predetermined code period corresponds to the length of the shortest code of said plurality of spreading codes.

Serial No.: 10/009,127

GAU: 2611

4. (Canceled).

9. (Previously Presented) A method for performing an interference estimation in a spread spectrum system using a plurality of spreading codes with different code lengths, comprising the steps of:

- a) receiving a spread spectrum signal;
- b) generating a despread sample signal by averaging over a predetermined code period over which said plurality of spreading codes are orthogonal; and
- c) calculating a variance estimate based on said despread sample signal;

wherein said variance estimate is a minimum variance unbiased (MVU), calculated in accordance with a relationship:

$$\hat{\sigma}^2 = E(|X|^2) - |E(X)|^2;$$

wherein  $\hat{\sigma}^2$  denotes said variance estimate for a symbol  $i$  of said received spread spectrum signal,  $X$  denotes said despread sample signal,  $E(X)$  denotes an expectation value for said despread sample signal, and  $E(|X|^2)$  denotes a mean power of said despread sample signal; and

wherein said despread sample signal is generated based on a relationship:

$$X(n) = \frac{1}{m} \sum_{k=1}^m r(k);$$

wherein  $m$  denotes a number of chips of said predetermined code period,  $k$  denotes a chip index of a spreading code of said received spread spectrum signal,  $r(k)$  denotes a value of a signal, obtained by removing said spreading code from said received spread spectrum signal, at said chip index  $k$ , and  $X(n)$  denotes the value of said despread sample signal at a sample index  $n$ .

Serial No.: 10/009,127

GAU: 14 2611

6. (Currently Amended) A method for performing an interference estimation in a spread spectrum system using a plurality of spreading codes with different code lengths, comprising the steps of:

- a) receiving a spread spectrum signal;
- b) generating a despread sample signal by averaging over a predetermined code period over which said plurality of spreading codes are orthogonal; and
- c) calculating a variance estimate based on said despread sample signal;

wherein said variance estimate is a minimum variance unbiased (MVU), calculated in accordance with a relationship:

$$\hat{\sigma}^2 = E(|X|^2) - |E(X)|^2;$$

wherein  $\hat{\sigma}^2$  denotes said variance estimate for a symbol  $i$  of said received spread spectrum signal,  $X$  denotes said despread sample signal,  $E(X)$  denotes an expectation value for said despread sample signal, and  $E(|X|^2)$  denotes a mean power of said despread sample signal; and

wherein said expectation value is obtained based on a relationship:

$$E(X) = \frac{1}{c/m} \sum_{n=1}^{c/m} X(n);$$

wherein  $c$  is a value proportional to ~~denotes~~ a spreading code length of said received spread spectrum signal,  $m$  denotes a number of chips of said predetermined code period and is a value proportional to a minimum spreading code length,  $n$  denotes a sample index of said despread sample signal, and  $X(n)$  denotes a value of said despread sample signal at the sample index  $n$ .

18  
7. (Currently Amended) A method for performing an interference estimation in a spread spectrum system using a plurality of spreading codes with different code lengths, comprising the steps of:

Serial No.: 10/009,127

GAU: 2611

- a) receiving a spread spectrum signal;
- b) generating a despread sample signal by averaging over a predetermined code period over which said plurality of spreading codes are orthogonal; and
- c) calculating a variance estimate based on said despread sample signal;

wherein said variance estimate is a minimum variance unbiased (MVU), calculated in accordance with a relationship:

$$\hat{\sigma}^2 = E(|X|^2) - |E(X)|^2;$$

wherein  $\hat{\sigma}^2$  denotes said variance estimate for a symbol  $i$  of said received spread spectrum signal,  $X$  denotes said despread sample signal,  $E(X)$  denotes an expectation value for said despread sample signal, and  $E(|X|^2)$  denotes a mean power of said despread sample signal; and

wherein said mean power of said despread sample signal is obtained based on a relationship:

$$E(|X|^2) = \frac{1}{c/m} \sum_{n=1}^{c/m} |X(n)|^2;$$

wherein  $c$  is a value proportional to denotes a spreading code length of said received spread spectrum signal,  $m$  denotes a number of chips of said predetermined code period and is a value proportional to a minimum spreading code length,  $n$  denotes a sample index of said despread sample signal, and  $X(n)$  denotes a value of said despread sample signal at the sample index  $n$ .

21  
 8. (Currently Amended) A method for performing an interference estimation in a spread spectrum system using a plurality of spreading codes with different code lengths, comprising the steps of:

- a) receiving a spread spectrum signal;

Serial No.: 10/009,127

GAU: 2611

b) generating a despread sample signal by averaging over a predetermined code period over which said plurality of spreading codes are orthogonal; and

c) calculating a variance estimate based on said despread sample signal;

wherein said variance estimate is a minimum variance unbiased (MVU), calculated in accordance with a relationship:

$$\hat{\sigma}^2 = E(|X|^2) - |E(X)|^2;$$

wherein  $\hat{\sigma}^2$  denotes said variance estimate for a symbol  $i$  of said received spread spectrum signal,  $X$  denotes said despread sample signal,  $E(X)$  denotes an expectation value for said despread sample signal, and  $E(|X|^2)$  denotes a mean power of said despread sample signal; and

wherein the interference estimate is obtained based on a relationship:

$$\hat{I} = m \frac{c+m}{c} \cdot \frac{1}{N} \sum_{i=1}^N I(i);$$

wherein  $\hat{I}$  denotes said interference estimate,  $c$  is a value proportional to a spreading code length of said received spread spectrum signal,  $m$  denotes a number of chips of said predetermined code period and is a value proportional to a minimum spreading code length,  $N$  denotes a number of averaged symbols of said received spread spectrum signal, for which said variance estimation is performed.

8  
9. (Previously Presented) The method according to claim 1, wherein said spread spectrum system is a WCDMA system.

23  
10. (Previously Presented) An apparatus for performing an interference estimation in a spread spectrum system using a plurality of spreading codes with different code lengths comprising:

a) receiving means for receiving a spread spectrum signal;

Serial No. 10/009,127

GAU: 2611

b) sampling means for generating a despread sample signal by averaging over a predetermined code period over which said plurality of spreading codes are orthogonal; and

c) estimation means for obtaining a variance estimate based on said despread sample signal;

wherein said estimation means comprises a first integration means for integrating said despread sample signal over a spreading code length of said received spread spectrum signal, a second integration means for integrating a signal corresponding to a power of said despread sample signal over said spreading code length, and subtracting means for subtracting a signal obtained by squaring an output signal of said first integrating means from an output signal of said second integrating means, wherein said estimation means comprises an averaging means for averaging an output signal of said subtracting means over a predetermined number of symbols of said received spread spectrum signal.

<sup>24</sup>  
~~11~~. (Previously Presented) The apparatus according to claim <sup>23</sup>~~10~~, wherein said predetermined code period corresponds to a length of a shortest spreading code of said plurality of spreading codes.

<sup>30</sup>  
~~12~~. (Previously Presented) The apparatus according to claim <sup>23</sup>~~10~~, wherein said sampling means comprises an integrating means for integrating a signal, obtained by removing a spreading code from said received spread spectrum signal, over said predetermined code period.

13. (Canceled).

14. (Canceled).

<sup>35</sup>  
~~15~~. (Previously Presented) The apparatus according to claim <sup>23</sup>~~10~~, wherein said averaging means comprises an integrating means.

<sup>38</sup>  
~~16~~. (Previously Presented) The apparatus according to claim <sup>23</sup>~~10~~, wherein said averaging means comprises a digital filter.

Serial No. 10/009,127

GAU: 2611

~~17~~<sup>41</sup> (Previously Presented) The apparatus according to claim ~~10~~<sup>23</sup>, wherein said interference estimation apparatus is an SIR estimator used for performing power control in a spread spectrum transceiver.

~~18~~<sup>43</sup> (Previously Presented) The apparatus according to claim ~~10~~<sup>23</sup>, wherein said spread spectrum system is a WCDMA system.

19. (Canceled).

20. (Canceled).

21. (Canceled).

~~22~~<sup>3</sup> (Previously Presented) The method according to claim 2, wherein said variance estimate is a minimum variance unbiased (MVU), calculated in accordance with a relationship:

$$\hat{\sigma}^2 = E(|X|^2) - |E(X)|^2;$$

wherein  $\hat{\sigma}^2$  denotes said variance estimate for a symbol  $i$  of said received spread spectrum signal,  $X$  denotes said despread sample signal,  $E(X)$  denotes an expectation value for said despread sample signal, and  $E(|X|^2)$  denotes a mean power of said despread samples signal.

~~23~~<sup>6</sup> (Previously Presented) The method according to claim ~~3~~<sup>5</sup>, wherein said variance estimate is a minimum variance unbiased (MVU), calculated in accordance with a relationship:

$$\hat{\sigma}^2 = E(|X|^2) - |E(X)|^2;$$

wherein  $\hat{\sigma}^2$  denotes said variance estimate for a symbol  $i$  of said received spread spectrum signal,  $X$  denotes said despread sample signal,  $E(X)$  denotes an expectation value for said despread sample signal, and  $E(|X|^2)$  denotes a mean power of said despread samples signal.

Serial No.: 10/009,127

GAU: 2611

24. (Currently Amended) The method according to claim 9, wherein said expectation value is obtained based on a relationship:

$$E(X) = \frac{1}{c/m} \sum_{n=1}^{c/m} X(n);$$

wherein c is a value proportional to ~~denotes~~ a spreading code length of said received spread spectrum signal, m denotes a number of chips of said predetermined code period and is a value proportional to a minimum spreading code length, n denotes a sample index of said despread sample signal, and X(n) denotes a value of said despread sample signal at the sample index n.

25. (Currently Amended) The method according to claim 9, wherein said mean power of said despread sample signal is obtained based on a relationship:

$$E(|X|^2) = \frac{1}{c/m} \sum_{n=1}^{c/m} |X(n)|^2;$$

wherein c is a value proportional to ~~denotes~~ a spreading code length of said received spread spectrum signal, m denotes a number of chips of said predetermined code period and is a value proportional to a minimum spreading code length, n denotes a sample index of said despread sample signal, and X(n) denotes a value of said despread sample signal at the sample index n.

26. (Currently Amended) The method according to claim 14, wherein said mean power of said despread sample signal is obtained based on a relationship:

$$E(|X|^2) = \frac{1}{c/m} \sum_{n=1}^{c/m} |X(n)|^2;$$

wherein c is a value proportional to ~~denotes~~ a spreading code length of said received spread spectrum signal, m denotes a number of chips of said predetermined code period and is a value proportional to a minimum spreading code length, n denotes a sample index of said despread sample signal, and X(n) denotes a value of said despread sample signal at the sample index n.



Serial No.: 10/009,127

GAU: 2611

<sup>12</sup>  
~~27~~ (Currently Amended) The method according to claim <sup>9</sup>~~8~~, wherein the interference estimate is obtained based on a relationship:

$$\hat{I} = m \frac{c+m}{c} \cdot \frac{1}{N} \sum_{i=1}^N I(i);$$

wherein  $\hat{I}$  denotes said interference estimate,  $c$  is a value proportional to a spreading code length of said received spread spectrum signal,  $m$  denotes a number of chips of said predetermined code period and is a value proportional to a minimum spreading code length,  $N$  denotes a number of averaged symbols of said received spread spectrum signal, for which said variance estimation is performed.

<sup>16</sup>  
~~28~~ (Currently Amended) The method according to claim <sup>14</sup>~~6~~, wherein the interference estimate is obtained based on a relationship:

$$\hat{I} = m \frac{c+m}{c} \cdot \frac{1}{N} \sum_{i=1}^N I(i);$$

wherein  $\hat{I}$  denotes said interference estimate,  $c$  is a value proportional to a spreading code length of said received spread spectrum signal,  $m$  denotes a number of chips of said predetermined code period and is a value proportional to a minimum spreading code length,  $N$  denotes a number of averaged symbols of said received spread spectrum signal, for which said variance estimation is performed.

<sup>19</sup>  
~~29~~ (Previously Presented) The method according to claim <sup>18</sup>~~7~~, wherein the interference estimate is obtained based on a relationship:

$$\hat{I} = m \frac{c+m}{c} \cdot \frac{1}{N} \sum_{i=1}^N I(i);$$

wherein  $\hat{I}$  denotes said interference estimate,  $m$  denotes a number of chips of said predetermined code period,  $N$  denotes a number of averaged symbols of said received spread spectrum signal, for which said variance estimation is performed.

Serial No.: 10/009,127

GAU: 2611

~~30~~<sup>4</sup> (Previously Presented) The method according to claim ~~2~~<sup>5</sup>, wherein said spread spectrum system is a WCDMA system.

~~31~~<sup>7</sup> (Previously Presented) The method according to claim ~~3~~<sup>5</sup>, wherein said spread spectrum system is a WCDMA system.

32. (Canceled)

~~33~~<sup>13</sup> (Previously Presented) The method according to claim ~~5~~<sup>9</sup>, wherein said spread spectrum system is a WCDMA system.

~~34~~<sup>17</sup> (Previously Presented) The method according to claim ~~6~~<sup>14</sup>, wherein said spread spectrum system is a WCDMA system.

~~35~~<sup>20</sup> (Previously Presented) The method according to claim ~~7~~<sup>18</sup>, wherein said spread spectrum system is a WCDMA system.

~~36~~<sup>22</sup> (Previously Presented) The method according to claim ~~8~~<sup>21</sup>, wherein said spread spectrum system is a WCDMA system.

~~37~~<sup>25</sup> (Previously Presented) The apparatus according to claim ~~11~~<sup>24</sup>, wherein said sampling means comprises an integrating means for integrating a signal, obtained by removing a spreading code from said received spread spectrum signal, over said predetermined code period.

~~38~~<sup>26</sup> (Previously Presented) The apparatus according to claim ~~11~~<sup>24</sup>, wherein said estimation means comprises a first integration means for integrating said despread sample signal over a spreading code length of said received spread spectrum signal, a second integration means for integrating a signal corresponding to a power of said despread sample signal over said spreading code length, and subtracting means for subtracting a signal obtained by squaring an output signal of said first integrating means from an output signal of said second integrating means.

~~39~~<sup>31</sup> (Previously Presented) The apparatus according to claim ~~12~~<sup>30</sup>, wherein said estimation means comprises a first integration means for integrating said despread sample signal over a spreading code length of said received spread spectrum signal, a second integration means for

Serial No.: 10/009,127

GAU: 2611

integrating a signal corresponding to a power of said despread sample signal over said spreading code length, and subtracting means for subtracting a signal obtained by squaring an output signal of said first integrating means from an output signal of said second integrating means.

<sup>27</sup>  
~~40~~. (Previously Presented) The apparatus according to claim <sup>24</sup>~~11~~, wherein said estimation means comprises an averaging means for averaging an output signal of said subtracting means over a predetermined number of symbols of said received spread spectrum signal.

<sup>32</sup>  
~~41~~. (Previously Presented) The apparatus according to claim <sup>30</sup>~~12~~, wherein said estimation means comprises an averaging means for averaging an output signal of said subtracting means over a predetermined number of symbols of said received spread spectrum signal.

42. (Canceled)

<sup>28</sup>  
~~43~~. (Previously Presented) The apparatus according to claim <sup>24</sup>~~11~~, wherein said interference estimation apparatus is an SIR estimator for performing power control in a spread spectrum transceiver.

<sup>33</sup>  
~~44~~. (Previously Presented) The apparatus according to claim <sup>30</sup>~~12~~, wherein said interference estimation apparatus is an SIR estimator for performing power control in a spread spectrum transceiver.

45. (Canceled)

<sup>44</sup>  
~~46~~. (Previously Presented) The apparatus according to claim <sup>23</sup>~~10~~, wherein said interference estimation apparatus is an SIR estimator for performing power control in a spread spectrum transceiver.

<sup>36</sup>  
~~47~~. (Previously Presented) The apparatus according to claim <sup>35</sup>~~15~~, wherein said interference estimation apparatus is an SIR estimator for performing power control in a spread spectrum transceiver.

Serial No. 10/009,127

GAU: 2611

<sup>39</sup>  
~~48~~ (Previously Presented) The apparatus according to claim <sup>38</sup>~~16~~, wherein said interference estimation apparatus is an SIR estimator for performing power control in a spread spectrum transceiver.

<sup>29</sup>  
~~49~~ (Previously Presented) The apparatus according to claim <sup>24</sup>~~11~~, wherein said spread spectrum system is a WCDMA system.

<sup>74</sup>  
~~50~~ (Previously Presented) The apparatus according to claim <sup>30</sup>~~12~~, wherein said spread spectrum system is a WCDMA system.

~~51~~ (Canceled).

<sup>45</sup>  
~~52~~ (Previously Presented) The apparatus according to claim <sup>23</sup>~~10~~, wherein said spread spectrum system is a WCDMA system.

<sup>37</sup>  
~~53~~ (Previously Presented) The apparatus according to claim <sup>35</sup>~~15~~, wherein said spread spectrum system is a WCDMA system.

<sup>40</sup>  
~~54~~ (Previously Presented) The apparatus according to claim <sup>38</sup>~~16~~, wherein said spread spectrum system is a WCDMA system.

<sup>42</sup>  
~~55~~ (Previously Presented) The apparatus according to claim <sup>41</sup>~~17~~, wherein said spread spectrum system is a WCDMA system.

**This Page is Inserted by IFW Indexing and Scanning  
Operations and is not part of the Official Record**

**BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☒ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☒ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:**

**IMAGES ARE BEST AVAILABLE COPY.**

**As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.**